



## Parts Description




**Cable Loc** - High security metal cylinder that attaches with a Screw Lock to the end of the cable. Can be keyed alike with any other BMS product.




**Pad Loc** - "Pass Through" High security pad lock that can be locked as a regular pad lock or have a security cable pass through it to create a security loop as an anchor.



**Security Cable** - 3/16" diameter steel cable. Nylon coated 1/4" diameter. Color: Apple gray. Made in 3, 4, 5, 6, 7, and 8 foot lengths, or in special lengths made to order.




**Cable Plate** - A 2" x 3.5" metal plate with high bonding adhesive (rated at 140 lbs. PSI) used to attach a Security Cable to a flat surface. The Cable Plate will attach to most surfaces of any equipment or work space.




**Cable Nut** - Metal tube can attach to an exposed case screw which will protect internal components on a CPU, or secure a TV or Monitor. Can also be used as an anchor for a Cable.




**Flex Pads** - A Cable Nut attached to a steel disk completely encased in neoprene. This part is flexible, can be trimmed to size and will permanently bond to a flat OR curved surface with cyanoacrylate (glue sold separately).




**Mouse Trap** - A 'U' shaped metal device designed to entrap a mouse, keyboard, and/or other data cable. Used in conjunction with a BMS Security Cable.



**Looper** - 14 gauge steel plate designed to allow a BMS Security Cable to loop around a fixed object.




**Hook Loc** - The unique Hook Loc will easily attach the security cable to Laptop computers, LCD projectors and any other product that has a micro security slot built into it.



### Screw Assortment

A. #6 x 5/8 B point sheet metal screws.  
B. #8 x 1" sheet metal screws.




**Security/LCD Clip** - A 'U' shaped metal device designed to secure projectors with a security bar. Used in conjunction with Security Cable.




# Cable Kit Installation Manual

\* Parts Description on Back Page


## Attaching Cable Lock




Unscrew the key inside the lock counter clockwise until out.



Put the end of the cable inside the lock counter inside the opposite side off the lock




Push the cable into the outer hole until snug, leaving the center open.




With the cable still in position screw the key in clockwise until snug.


## Attaching Pad Lock




To lock, insert cable into closed hole while turning the key, then release key.



To pass through, insert the cable into the bottom of the open hole




Push the cable through and then wrap around an anchor point.




Insert end of cable into the closed hole while turning the key, then release key to lock.

## Attaching Cable Plate



Once you have chosen the position of the Cable Plate on the component, pull off the plastic cover from the back of the plate.



Attach the Cable Plate to the chosen position on the component by pressing against it on all areas of the surface to ensure a complete bonding.

# Contact Business Machine Security

Customer Service - (800) 872-9562

Technical Support - [customerservice@locdown.com](mailto:customerservice@locdown.com)

Web site - [www.LocDown.com](http://www.LocDown.com)

